


FEATURES & BENEFITS

ALTERNATIVE

Mounting the proximity switch to the ball valve is an alternative to using a flow switch plumbed in to the water supply.

OPTIONS

For more information, visit www.hawsco.com or call (888) 640-4297.



SPECIFICATIONS

The Haws SP152DC contains two double pole proximity switches designed to mount to a Haws emergency shower and eyewash. Mounted to the ball valve, each switch sends an electrical signal to an alarm or control board when the emergency fixture is activated. This switch kit includes the electrical sensor, magnet and mounting hardware.

APPLICATIONS

Specifically, this proximity switch can be used for most Haws emergency eyewashes and drench showers (not meant for freeze resistant models).

N 10

DOW CORNING LUBRICANT #111 (0003247000)

LOCTITE THREAD LOCKER 222MS (0003244389)

SCREW, 3/8-24 X 1 W/HOLE

9 ω ~ တ S 4 ယ

WASHER, FLAT, 3/8

N

N

N

2 4 N N 4 4 ł 2

N

SHOWN FOR REFERENCE HAWS 8300-8309

NOT SUPPLIED

4 N N 4 4 N ł

NUT, 3/8-24

MAGNET, PROXIMITY SWITCH

JAM NUT, 5/8-18, PROXIMITY SWITCH

N

SCREW, 1/4-20 X 1-1/4

NUT, 1/4-20

0

NOTES

- APPLY SMALL AMOUNT OF THREAD LOCKER (LOCTITE #222MS SUPPLIED) TO MALE THREADS, WHERE INDICATED.
- 2 APPLY SMALL AMOUNT OF LUBRICANT (DOW CORNING #111 - SUPPLIED) TO PROXIMITY SWITCH (ITEM 1) THREADS, PRIOR TO INSTALLATION (PREVENTS THREAD SEIZING).

(SEE SHEET 2)

ယ THESE PROXIMITY SWITCHES ARE CSA CERTIFIED AS ACCESSORIES FOR USE IN HAWS MANUFACTURED ASSEMBLIES.











PROXIMITY SWITCH INSTALLATION LOCATIONS:
- SINGLE PROXIMITY SWITCH MODELS SP152S AND SP152D CAN BE INSTALLED AT EITHER:

4

A) A SHOWER HEAD ONLY (SEE SHEET 2 OF 5, DETAIL A), OR B) AN EYE/FACE WASH ONLY (SEE SHEET 2 OF 5, DETAIL B AND SHEET 3 OF 5)

DOUBLE PROXIMITY SWITCH MODELS SP152SC AND SP152DC

CAN BE INSTALLED AT:
A) BOTH A SHOWER HEAD AND EYE/FACE WASH ON COMBINATION
SAFETY SHOWER UNITS (SEE SHEET 2 OF 5, DETAILS A AND B AND SHEET 3 OF 5).

Ò PROXIMITY SWITCH KIT BRACKETS WILL FIT 1/2" - 1" IPS PIPE SIZES. SEE HAWS MODEL COMPATIBILITY TABLE ON PAGE 3 OF HAWS SP152 SERIES OPERATION AND MAINTENANCE MANUAL, FOR MODELS THAT THESE KITS WILL FIT ON.

ITEM No.

MODEL NUMBER

PARTS BREAKDOWN

SP152S SP152D SP152SC SP152DC

DESCRIPTION

QTY.

QTY.

QTY.

QTY.

N

STRAP, PROXIMITY SWITCH

N ł

N

N

PROXIMTY SWITCH, DPDT PROXIMITY SWITCH, SPDT


WASHER, FLAT, 1/4

E C.V.		
DE VED		
N. BY	J	
	1	
30000		
9	3	
	7	
	9	
	g	
	•	
	SF (775) 3: E-MAI WEBS	

1455 KLEPPE LANE SPARKS, NEVADA 89431) 359-4712 FAX (775) 359-7424 MAIL: HAWS@HAWSCO.COM

| MODEL(S) | SP152S/SP152D/SP152SC/SP152DC/SP155-PS HAWSCO.COM 0510001049.D

2022 Haws Corporation - All Rights Reserved. HAWS® and other trademarks used in these materials are the exclusive property of Haws Corporation SEE SHEET 4 OF 5 FOR ELECTRICAL OF PROXIMITY SWITCH(ES) WIRING





FOR MODELS 7324 OR 8317 SHOWN.
SEE PREVIOUS SHEET (2 OF 5) FOR ALL OTHER INSTALLATIONS.

© 2022 Haws Corporation - All Rights Reserved. HAWS® and other trademarks used in these materials are the exclusive property of Haws Corporation.

| MODEL(S) | SP152S/SP152D/SP152SC/SP152DC/SP155-PS

0510001049.D






ALL ELECTRICAL INSTALLED PER LOCAL ELECTRICAL CODES

Proximity Switches rated to 3Amps DC, Voltage 0-28VDC or 0-120VAC 100VA. Ambient Temperature -40° C to +60° C.

WIRING DIAGRAM FOR SP155-PS





1455 KLEPPE LANE
SPARKS, NEVADA 89431
(775) 359-4712 FAX (775) 359-7424
E-MAIL: HAWS@HAWSCO.COM

0510001049.D